

## FC Series Manual Speed Control

Model: FC-1VAC

### *An inexpensive control for variable speed fans or heat lamps*

The Manual Speed Control is a simple and effective way to control fan motors. The FC-1VAC allows you to manually adjust the speed of ventilation or heating equipment. It can also be used as a light dimmer for brooder heat lamps and can power up to five 250-watt lamps.

The FC-1VAC is ideal for poultry, livestock, greenhouse, or light industrial buildings.

### Features

- One variable output
- ON/OFF switch
- Adjustable HIGH/LOW settings
- Overload protection fuse
- NEMA 4X enclosure (corrosion resistant, water resistant, and fire retardant)
- CSA approval
- Limited warranty (2 years)

### Electrical ratings

- **Input** 120/230 VAC, 50/60 Hz
- **Variable stage** 12.5 A at 120/230 VAC, general-purpose (resistive) \*\*  
9 FLA at 120/230 VAC, PSC motor  
1/2 HP at 120 VAC, 1 HP at 230 VAC, PSC motor  
1500 W tungsten at 120 VAC
- **Variable fuse** 15 A, 250 VAC ABC-type ceramic

### Additional information

For more information about the FC-1VAC or other Phason products, contact your dealer or visit [www.phason.ca](http://www.phason.ca).

