
# CCM2-0803P-A3U2

# **Capacitive Proximity Sensor**



#### **Dimensions**



Note: The product images shown may change over time as products are updated.


### Part Number

### CCM2-0803P-A3U2

#### Features

- · Capacitive sensors for the reliable detection of liquids, plastics, powders, pellets and pastes
- · Available in plastic or stainless steel housings
- Connectable with a pre-wired cable of any • length or with a quick-connector
- Available with PNP, NPN, AC or AC/DC output functions
- Mountable with a shielded or unshielded • construction with adjustable sensitivity

#### Connection



## **Technical Data**

| Sensing Type               | Capacitive Sensor                                   |
|----------------------------|---|
| Body Style                 | Cylindrical   |
| Sensor Housing Material    | Chrome Plated Brass                                 |
| Sensor Face Material       | PBT   |
| Mounting Style             | Non-Shielded  |
| Diameter                   | 8 mm  |
| Sensing Range:             | 3 mm  |
| Output Type:               | PNP   |
| Output Function            | Normally Open                                       |
| Connection                 | Pre-Wired Cable                                     |
| Body Length                | 45  |
| Operating Voltage          | 10-30 VDC   |
| Switching Frequency        | 100 Hz  |
| Operating Temperature      | -25 °C - +70 °C                                     |
| Overload Trip Point        | 220 mA  |
| Hysteresis:                | <15% (Sr)   |
| IP Rating:                 | IP67  |
| Shock Rating:              | IEC 60947-5-2, Part 7.4.1/IEC 60947-5-2, Part 7.4.2 |
| Short Circuit Protected    | YES   |
| Reverse Polarity Protected | YES   |
| Connector Type             | N_A   |
| Current Consumption        | <10 mA  |
|                            |   |



In the USA: 1889 Maryland Ave., Niagara Falls, NY 14305 In Canada: 3419 Mainway, Burlington, ON L7M 1A9 Toll Free: 1-800-644-1756 • Fax: 888-283-2127 SENSORS service@htmsensors.com

htmsensors.com