
## **Inductive Proximity Sensor**



Note: The product images shown may change over time as products are updated.

# Part Number FCP1-1805N-ARU4Z

# Features

Inductive Proximity Sensors are used in a wide variety of manufacturing operations where a metal target needs to be sensed. HTM Sensors inductive proximity sensors have a Lifetime Warranty, a CSA or UL approval, and a huge inventory for sameday shipping. For tougher applications where the sensors need more range to stay out of harm's way, or to withstand high temperatures, weld spatter, chemical exposure, oil or other rough environments, HTM Sensors has the widest range of proximity sensors on the market.


#### Connection

- 1 Brown
- 2 Not Used 3 - Blue
- 4 Black





### **Dimensions**



Body Length (mm) 73

T-	_  _	:-		Da	4_
10	rn	nıc	ובי	112	тэ

Tooliilloan Bata			
Body Style	Cylindrical		
Sensor Housing Material	PBT Plastic		
Sensor Face Material	PBT Plastic		
Mounting Style	Shielded		
Diameter	18 mm Threaded		
Sensing Range:	5 mm Range		
Output Type:	NPN Output		
Output Function	Normally Open Output		
Connection	4-Pin Connector		
Connector Type	M12x1 Quick-Connect		
Operating Voltage	10-30 VDC		
Switching Frequency	1 KHz		
Operating Temperature	-25 °C – +70 °C		
Current Consumption	<10 mA		
IP Rating:	IP68		
EMC Rating	RFI>3V/m / EFT>1kV / ESD>4Kv (contact)		
Shock Rating:	IEC 60497-5-2 Part 7.4.1&7.4.2		
Short Circuit Protected	Yes		
Reverse Polarity Protected	Yes		
Max Current	200 mA		
Leakage Current	<0.01 mA		
Surge Current	-		
Response Time	0.2 ms/0.2 ms		
Hysteresis	<15%(Sr)		
Overload Trip Point	≥220 mA		
Weld Field Immune	No		
Weld Spatter Resistant	No		
Body Length (mm)	73		



In the USA: 1889 Maryland Ave., Niagara Falls, NY 14305 In Canada: 3419 Mainway, Burlington, ON L7M 1A9 Toll Free: 1-800-644-1756 • Fax: 888-283-2127 service@htmsensors.com