## FCU2-1808C-BZU4

### Inductive Proximity Sensor



Dimensions

**Technical Data** 

Sensor Housing Material

Sensor Face Material

Mounting Style

Sensing Range:

**Output Function** 

Connector Type

**Operating Voltage** 

Switching Frequency

**Operating Temperature Current Consumption** 

Short Circuit Protected

**Reverse Polarity Protected** 

Output Type:

Connection

IP Rating:

**EMC** Rating

Shock Rating:

Max Current

Leakage Current Surge Current

**Response Time** Hysteresis


**Overload Trip Point** Weld Field Immune

Body Length (mm)

Weld Spatter Resistant

Diameter

Body Style



Body Length (mm) 99


Note: The product images shown may change over time as products are updated.

# Part Number FCU2-1808C-BZU4

Inductive Proximity Sensors are used in a wide sensors need more range to stay out of harm's way, chemical exposure, oil or other rough environments,

### Connection





Cylindrical

**PBT** Plastic

Unshielded

8 mm Range

18 mm Threaded

DC 2-Wire Output

4-Pin Connector

10-60 VDC

500 Hz -25 °C - +70 °C

IP67

Yes

Yes

\_

No

No

99

100 mA <0.8 mA

0.5 ms/0.5 ms

<15%(Sr) >120 mA

Mini Quick-Connect

Normally Closed Output

RFI>3V/m / EFT>1kV / ESD>4Kv (contact)

IEC 60497-5-2 Part 7.4.1&7.4.2

Stainless Steel SUS303

F	ea	ατι	Ire	es	

variety of manufacturing operations where a metal target needs to be sensed. HTM Sensors inductive proximity sensors have a Lifetime Warranty, a CSA or UL approval, and a huge inventory for sameday shipping. For tougher applications where the or to withstand high temperatures, weld spatter, HTM Sensors has the widest range of proximity sensors on the market.

Μ	In the USA: 1 In Canada: 3 Toll Free: 1-8	
NSORS	service@htm	

SE

889 Maryland Ave., Niagara Falls, NY 14305 419 Mainway, Burlington, ON L7M 1A9 300-644-1756 • Fax: 888-283-2127 sensors.com

### htmsensors.com