# **ARLP88-KIT**

- · Works on all Adams Rite 8800 series
- EASY INSTALLATION
- Cost-effective latch retraction
- · AVAILABLE IN 12V OR 24V







The new ARLP88-KIT is a incredibly easy field installable solenoid latch retraction kit for Adams Rite 8800 series exit devices. The only hole you'll need to drill is the raceway! It's an ideal solution for latch retraction on a stairwheel device where cost is a concern. It can be prepped at the factory for 24V or 12V solenoids.

## **SPECIFICATIONS**

## Voltage:

- Input Voltage:24VAV/DC or 12VAC/DC+/- 10%
- Solenoid Amperage 12V: 900mA
- Solenoid Amperage 24V: 450mA
- Wire gauge: Minimum 18 gauge

#### Wire Run:

300' with 18ga wire

### **Product Details:**

Weight: 2 Lbs

#### **Device Cutdown Details:**

 36/42/48" - All the way to the back activting arm

#### **Accessories:** Additional Charge

ARREXKIT-ED - Field Installable REX Kit

#### INSTALL VIDEO



#### **Features:**

- Solenoid Latch Pullback Audible retraction
- High-Performance quality solenoids designed for demanding applications
- Extended duration latch pullback capability for "continuously on" conditions
- Low Current Draw
- Long wire run with 2-18ga wire Long wire runs provides installer with
  convenience of placing the Command
  locking hardware power supply in a
  centralized location; i.e. the same closet as
  the access control panel
- 5' cable with Quick Connect for solenoid to easily connect to power supply lead
- 3-year "no hassle" warranty



# **How to Order**

Part #	Easy Order #	Description	
ARLP88-KIT-24 ARLP88-KIT-12	79563 79562	Kit for Adams Rite 8800 series, EU 24V Kit for Adams Rite 8800 series, EU 12V	

# **ARLP88-KIT Matrix**

The ARLP88- KIT will work in new installations and as a replacement for installations with existing electrifications, matrix lists available options.



