EEB Emergency Exit Button

Redundant backup ensures safe egress



Install the EEB Emergency Exit Button next to the door to provide additional safety and redundancy as required by code when using a motion detector for a request to exit device.

NOTE: Securitron's UL294 certification indicates that when the EEB is used with the XMS Motion Sensor, it meets the NFPA Life Safety Code 101 requirements for exit of access-controlled egress doors.

Features

Standard Features

- Backup device in case of exit sensor failure per BOCA, NFPA, IBC, and VBC code
- Momentarily pressing the button releases the door for 30-seconds
- Re-triggerable for added
 30-second release
- Interchangeable green and red lenses included standard
- MagnaCare[®] lifetime replacement, no-fault, no questions asked warranty

Optional Features

- Single gang
- Narrow stile
- EEB2 includes standard lenses plus blue ADA lens
- Illumination kits

Specifications

Certifications (EEB2, EEB3N only)

- CSA-C22.2 No.205 Listed
- CSFM—California State Fire Marshal

Electrical

- 28 mA at 12 VDC
- 26 mA at 24 VDC
- 3A SPDT N/C Relay





How to Order

| MODEL SERIES | LED LENS COLOR | MOUNTING METHOD |
|------------------|----------------------|---------------------|
| EEB | 3 | Ν |
| EEB Push Buttons | 2 Green/Red/Handicap | (blank) Single Gang |
| | 3 Green/Red | N Narrow Stile |

NOTE: Not every combination above is possible. Please contact the factory if you need a combination of features not listed on this page

Updated 7/14/23 Printed in the U.S.A. Patent pending and/or patent www.assaabloydss.com/patents

Copyright © 2023, Hanchett Entry Systems, Inc., an ASSA ABLOY Group company. All rights reserved. Reproduction in whole or in part without the express written permission of Hanchett Entry Systems, Inc. is prohibited.